# **Your Solution Partner in Energy**

## **ALMCU 2500**









#### **Prime Power**

Refers to the main power supply, working under 70% average load for unlimited time. 10% overloading is allowed.

#### Stand-by Power

**Fuel Tank Capacity** 

Refers to the back up power supplied to the varying load for a limited time. Overloading is not allowed.

#### Generator

		Prime	Stand-by	
kVA		2000	2500	
kW		1600	2000	
ALMCU 2500				
Cummins / QSK60 G13				
Diesel				
50 Hz				
$\cos \Phi = 0.8$				
400/231 V				
	Wit	:h Canopy	Open Skid	
m	ım K 7	000	6400	
m	ım K 3	970	3400	
m	ım K 2	700	2500	
kg	g 165	500	14460	
	kW m	kW  With mm K 7 mm K 3 mm K 2	KW 1600  ALMCU 2500  Cummins / QSK60  Diesel  50 Hz  Cos Φ = 0.8  400/231 V  With Canopy  mm K 7000  mm K 3970  mm K 2700	

H 4000

H: External K: Container TBA: To be added

lt





H 4000

# **Your Solution Partner in Energy**

# **ALMCU 2500**

## GENERATOR

### Diesel Generating Sets

# AF

### Engine

Engine Manufacturer:		CUMMINS
Engine Model:		QSK60 G13
Engine Type:		4 Stroke Diesel Engine
Engine Stand-by Power:	kWm	2164
Engine Prime Power:	kWm	1727
Cylinder Arrangement:		16V
Displacement:	lt	60,2
Cooling System:		Water Cooling
Bore x Stroke:	mm	159 x 190
Compression Ratio:		14,5:1
Aspiration:		Turbocharger, Aftercooler
Governor Type:		Electronic
Electrical System:	VDC	24
Lubricant Oil Capacity:	lt	280
Coolant Capacity:	Lt	603
Frequency Lt:	Hz - rpm	50 - 1500
Jacket Water Heater:	Piece x W	TBA
Battery:	Piece x AH	TBA
Charge Alternator Current:	Α	55
Injection System:		Direct
Cooling Air Flow:	m³/min	1860
Combustion Air Flow:	m³/min	154,38
Exhaust Gas Flow:	m³/min	393,18
Exhaust Gas Temperature:	°C	507
Fuel Consumption Under 100% Load:	lt/h	399
Fuel Consumption Under 75% Load:	lt/h	302
Fuel Consumption Under 50% Load:	lt/h	210

### Alternator

	3/4+
	Self Excited, Brushless
	A.V.R. (Automatic)
	±%1
	Н
	IP23
	Star
Hz	50
	$Cos \Phi = 0.8$
	< % 3.5
VAC	231/400

TBA: To be added





# **Your Solution Partner in Energy**

## **ALMCU 2500**

### iesel Generating Sets

Control Panel







AMF9



ALM929

#### Alimar ALM-929 Automatic Control Module

AMF function
ATS function
Remote start function
Manual start function
Engine control function
Suitable for remote monitoring

#### Mains and Genset LL- LN Voltages

Mains and generator frequency
Mains and genset phase currents
Mains and generator neutral currents
Grid and generator phase and total, kW, kVA,kVAr
Power factor, engine speed, battery voltage and more

#### Connections

3 phase 4 wire, stars & delta 3 phase 3 wire, 2 current transformer

2 phase 3 wire

1 phase 2 wire

#### Communication

RS232 - 485 connection with cable J1939-CANBUS GSM / GPRS connection Ethernet connection Modbus RTU

#### **Protection Functions**

- Overvoltage
- Low voltage
- Voltage asymmetry and phase sequence
- High frequency
- Low frequency
- Short-circuit current
- Overcurrent
- Power factor
- Coolant temperature
- Low oil pressure

#### **Auto Panel Features**

- Automatic generator, grid control and fault monitoring
- Easy control with a user-friendly interface from the panel screen
- Remote operation with optional communication cards
- Manual programming with password-protected service interface
- Manual control of generator and transfer panel with buttons on the front panel
- Front panel protection class IP65
- With an operating temperature of -20 C to +70 C and a storage temperature of -40 C to +80 C





## **ALMCU 2500**

## Generating Sets

### Standard Features





Cabin: Alimar Generator cabins are user-friendly. It provides easy maintenance and repair. Cabin monitoring the control module from outside and emergency stop button can be accessed. The inner surface of the cabinets is sound and high intensity flame that provides heat insulation does not walk covered with sponge. Cabin paint is resistant to corrosion and rust. It is resistant to. Muffler hardware on certain models hidden inside the cabin.





#### **Engine**

Low fuel consumption and high performance latest technology diesel engines are used with electronic or mechanical governor, water-cooled radiator system, replaceable oil, fuel, air filters. Alternator

With its robust and compact structure, steel body, maintenance-free single bearing system, brushless, self-excited system and electronic type AVR, alternators suitable for the special needs of different applications are used.

**Gen-Set Canopy** 

Modular cabinets are used in accordance with 2000/14/EC directives, covered with sound and heat insulation flame-resistant sponge, corrosion and rust resistant paint, locks and hinges, large lockable doors on both sides for easy service and maintenance. Exhaust and silencer insulated according to engine suitability. Small and medium power fuel tank is designed as underchassis. Lifting ears on chassis. Vibration prevention wedges are used under the chassis. Standard Accessories

Industrial silencer and stainless steel compensator

Maintenance-free lead-acid starter battery, cable and stand

Jacket water heater with thermostat

Automatic control module

SMPS battery charger

Relays and fuses

Emergency stop button

#### Optionel Features

Remote radiator

Coolant level sensor

Fuel level sensor

Winding dehumidifier heater

Winding and bearing temperature sensors

MCCB PMG/AREP

#### Other Accessories

Electronic/Manual oil drain pump

Critical type silencer

Trailer

Main fuel tank stainless and insulated

Automatic transfer panel

Spring loaded seismic isolator

Oil and fuel tank heater

Maintenance tools and kits

